



Projected Capacitive Input (PCI) User Guide

Preface

Disclaimer

The information in this document is subject to change without notice. The manufacturer makes no representations or warranties regarding the contents of this manual and specifically disclaims any implied warranties of merchantability or fitness for any particular purpose. Furthermore, the manufacturer reserves the right to revise this publication or make changes in the specifications of the product described within it at any time without notice and without obligation to notify any person of such revision.

Trademarks

AMT, PenMount, Microsoft, Windows and other trademarks and product names used in this manual are the properties of their respective owners and are acknowledged.

Copyright

This publication, including all photographs, illustrations and software, is protected under international copyright laws, with all rights reserved. Neither this manual, nor any of the material contained herein, may be reproduced without the express written consent of the manufacturer.

Copyright 2014 © Apex Material Technology Corp. All rights reserved.

Revision Table

Date	Revision	Changes
2012/05	1.0	Initial
2012/09	1.1	Remove the word - "P2" in user guide
2014/03	1.2	Modify PenMount Utilities
2014/11	1.3	Textual refinement and editing

Table of Contents

Preface.....	i
Disclaimer.....	i
Trademarks	i
Copyright	i
Revision Table.....	i
Table of Contents.....	ii
Chapter 1 Introduction	1
1.1 About this manual	1
1.2 Projected capacitive touch panel	1
1.3 PenMount PCI control board	1
1.4 Drivers & utilities	1
1.5 Before using this manual	2
1.6 After-sales service	2
Chapter 2 Install Drivers for PenMount PCI Control Board	2
2.1 PenMount PCI Windows driver	2
2.1.1 Install PenMount PCI Windows driver in Windows 7	2
2.1.2 Uninstall PenMount PCI Windows driver in Window7	4
2.1.3 Install / uninstall PenMount PCI Linux X Window driver	5
2.1.4 Install / uninstall PenMount PCI WinCE Driver	5
Chapter 3 Configure the Touch Screen	5
3.1 Configure PenMount PCI RS-232/ USB in Windows XP	5
3.1.1 PenMount Control Panel	5
3.1.1.1 Device	5
3.1.1.2 Multiple Monitors	7
3.1.1.3 Tools	8
3.1.1.4 Screen Rotation Monitor	8
3.1.2 PenMount monitor menu icon	8
3.2 Configure PenMount PCI RS-232/USB In Windows Vista/7	9
3.2.1 PenMount Control Panel	9
3.2.1.1 Device	9
3.2.1.2 Tools	9
3.2.2 Multiple Monitors	9
Chapter 4 PenMount Utilities	10
4.1 PenMount utilities for Windows.....	10
4.1.1 PCIMSet	10
4.1.2 PCIQuickSet.....	11
4.1.3 PMUpdate	12
4.2 PenMount utilities for Linux.....	13
4.2.1 PCIMSet for Linux	13
4.2.2 PmFu for Linux	14
Chapter 5 Trouble Shooting.....	14

Chapter 1 Introduction

PenMount Projected Capacitive Input (PCI) control boards are designed to support projected capacitive touch panels. PenMount offers a series of PCI controller products. PenMount PCI controllers facilitate high precision touch activation and dual finger gesture recognition with minimum touch force required.

PenMount PCI control boards are built with the functions necessary to operate PCI touch smoothly. Customers can define their product functions and mechanical requirements by referring to this manual.

1.1 About this manual

This manual describes the features of PenMount PCI control boards, how to operate the utility, and how to install and use software drivers and utilities with your operating system.

This manual is for users using PenMount PCI control boards and software, as well as engineers who are integrating and customizing the PenMount PCI control board for use with other products.

1.2 Projected capacitive touch panel

AMT provides various sizes of standard PCI touch panels. Customers can find a matching PenMount controller for each PCI touch panel. If a PCI touch panel is custom designed, the designated PCI control board might be different. For any questions regarding connecting the control board to the touch panel, please check with your system manufacturer.

1.3 PenMount PCI control board

PenMount designs control boards for AMT projected capacitive touch panels. Different sizes of PCI touch panels are matched with different PenMount control boards. PenMount controller part numbers and their supported touch panels are as follows:

Part No.	Touch Screen Size
PM2101 COF	3" - 4.9"
PM2102 COF	3" - 4.9"
PM2201 COF	5" - 7.9"
PM1201A	5" - 7.9"
PM1300A	8.0" - 10.4"
PM1302	8.0" - 10.4"
PM1400A	11" - 15"
PM1401	11" - 15"
PM1500	15" - 18.5"

Remark: a. This chart is subject to change without prior notice.

b. Customized touch panels may be supported by different control boards, which are not listed here.

1.4 Drivers & utilities

All PenMount PCI control boards are bundled with software drivers and utilities that support the most common hardware platforms and operating systems.

PCIMSet is the initial setting utility for the PenMount PCI control board series. PCIMSet allows the user to adjust the controller input interface, touch panel orientation, and touch sensitivity, or check the firmware version. PenMount PCI drivers cannot be installed or operate when PCIMSet is in use. This utility is designed for system integrators and hardware designers. Thus, we do not recommend end users adjust PCI parameters with PCIMSet. End users can use the utility built into the PenMount driver instead.

After installing the PenMount PCI driver, the user can use other PenMount touch functions such as edge compensation and linearity test with the utility built in the driver. Please refer to the AMT or PenMount website for PenMount PCI control board drivers.

1.5 Before using this manual

Make sure the PCI touch panel and PenMount control board have been integrated properly into the computer system. If your need to integrate the control board and touch panel, please refer to the “AMT Projected Capacitive Touch Panel Integration Guide”.

1.6 After-sales service

The PenMount PCI control board series and software are updated on a regular basis. For more information on the latest updates, downloads, and technical support, please refer to our websites:

<http://www.amtouch.com.tw>

<http://www.penmount.com.tw>

Chapter 2 Install Drivers for PenMount PCI Control Boards

This chapter describes how to install drivers and other software that enables your PenMount PCI control boards to work with various operating systems. PenMount PCI control boards support the following connection interfaces:

Part No.	Interface			
	USB	RS-232	UART	I ² C
PM2101 COF			•	•
PM2102 COF		•	•	•
PM2201 COF	•		•	•
PM1201A	•	•		
PM1300A	•			
PM1302	•	•	•	•
PM1400A	•	•		
PM1401	•	•	•	•
PM1500	•	•	•	•

PenMount PCI drivers support the most common versions of Windows and Linux systems. Please visit our websites (<http://www.amtouch.com.tw> or <http://www.penmount.com.tw>) to see supported operating systems.

2.1 PenMount PCI Windows driver

PenMount provides drivers for the RS-232 and USB interfaces

(PenMount-Windows-Universal-Driver-V2.4.1.320WHQL). PenMount drivers can be used in Windows 2000/2003/2008/XP/Vista/7/8. For Windows Vista/7/8, the PenMount control board can be used directly with the built-in USB driver without having to install additional drivers.

2.1.1 Install PenMount PCI Windows driver in Windows 7

Before installing the driver, please connect the PenMount PCI controller via the RS-232 or USB interface. (The driver will be installed according to the interface you are using.) Then, decompress the file “PenMount-Windows-Universal-Driver-V2.4.1.320WHQL” and begin driver installation following the steps below:

Step 1: After extracting the files, run “Setup.exe” (Fig.1).

Step 2: When the setup wizard appears, click “Next” to continue (Fig.2).




Fig.1




Fig.2

Step 3: When the license agreement appears, click “I Agree” to continue (Fig.3).

Step 4: Select the destination folder and click “Install” (Fig.4).




Fig.3




Fig.4

Step 5: The dialog window “Would you like to use touch as mouse device?” will appear. If you would like to use PenMount touch functionality, click “Yes”; if you would like to use system touch gestures, click “No” (Fig.5).

Step 6: If you click “Yes” in step 5, the following window will pop up, indicating the installation is complete. Click “Finish” to exit the window (Fig.6).




Fig.5




Fig.6

When the installation is complete, the PenMount icon  will be displayed in the notification area.

If you click “No” in step 5, the following dialog window will appear. Click “Finish” to exit the window (Fig.7). When the installation is complete, the “PenMount Control Panel” icon will appear on the desk top (Fig.8).




Fig.7




Fig.8

2.1.2 Uninstall PenMount PCI Windows driver in Window7

Please follow the steps below to uninstall the PenMount PCI Windows driver:

Step 1: In “Control Panel”, choose “Uninstall or change a program”. Find “PenMount Windows Universal Driver V2.4.1.320 (WHQL)”, and click “Uninstall/Change” (Fig.9).

Step 2: When the following dialog window appears, click “Next” to remove the driver (Fig.10).




Fig.9




Fig.10

Step 3: The system will uninstall the driver (Fig.11).

Step 4: A dialog window will appear, indicating the driver has been uninstalled. Click “Finish” to exit (Fig.12).




Fig.11




Fig.12

2.1.3 Install / uninstall PenMount PCI Linux X Window driver

Before installing PenMount PCI Linux X Window Driver for PenMount control boards, you must have Linux X Window installed and running on your computer. You must also have a PenMount Serial Interface and either PM2101, PM2102, PM2201 PCI COF or PM1201A, PM1300A, PM1302, PM1400A, PM1401 and PM1500 control boards installed.

PenMount PCI Linux X Window Driver for PCI control boards support various operating systems. The supported Linux versions are listed on our website. Please visit <http://www.amtouch.com.tw> or <http://www.penmount.com.tw> to view the supported Linux versions.

Please refer to the readme file included in the driver folder for further details.

2.1.4 Install / uninstall PenMount PCI WinCE Driver


Before installing the PenMount WinCE Driver, you must have a WinCE system installed and running on your device. You must also have a PenMount Serial Interface such as PM2101, PM2102, PM2201 PCI COF or PM1201A, PM1300A, PM1302, PM1400A, PM1401 and PM1500 control boards installed.

Please see the readme file included in the driver folder for further details.

Chapter 3 Configure the Touch Screen

This section describes how to configure the PenMount device after it is installed to the windows operating environment. A PenMount driver provides various functions for testing and enhancing controller performance under the windows operating environment.

3.1 Configure PenMount PCI RS-232/ USB in Windows XP

Right-click on the PenMount monitor icon  in the notification area and select "Control Panel" from the menu to configure the touch screen. (Fig.13)

Open PenMount Control Panel. The PenMount PCI USB icon can be accessed under the "Device" tab. In the Device tab, you can see the devices detected on your system. Select a device and press "Configure" to set the configuration. (Fig.14)



Fig.13




Fig.14

3.1.1 PenMount Control Panel

The "PenMount Control Panel" functions are described below.

3.1.1.1 Device

In this tab, you can see how many devices are detected on your system. Select any device by clicking on its icon. (Fig.15)




Fig.15

a. Setting

Operation Mode	<p>This mode enables and disables the mouse's ability to drag on-screen icons—useful for configuring POS terminals.</p> <p>Pen Input Emulation – When this mode is selected, the mouse will emulate Windows Vista pen input device operation. No mouse event will be sent until the touch is dragged out of range or released from the screen.</p> <p>Click on Touch – When this mode is selected, the mouse only provides the click function; dragging is disabled.</p> <p>Mouse Emulation – When this mode is selected, the mouse functions as normal and allows dragging of icons.</p> <p>Click on Release – When this mode is selected, the mouse only provides a click function when the touch is released.</p>
Beep Sound	<p>Beep Sound checkbox– Enables/disables beep function.</p> <p>Beep on pen down – Beep occurs when the pen comes down.</p> <p>Beep on pen up – Beep occurs when the pen is lifted.</p> <p>Beep on both – Beep occurs both when the pen comes down and when it is lifted up.</p> <p>Beep Frequency – Modifies sound frequency.</p> <p>Beep Duration – Modifies sound duration.</p> <p>Kind of Sound – Selects beep sound type.</p>
Cursor Stabilizer checkbox	Enables/disables the function which prevents cursor shaking.
Use press and hold as right click	You can set the time out and area to your needs.

b. Edge Compensation

This page contains the edge compensation settings for advanced calibration. You can adjust the settings from 0 to 30 to accommodate differences in touch panels. If the edge area has difficulty detecting touch, please increase this value. If the sensing point shifts too much in the edge area, please decrease this value. (Fig.16)

c. About

This tab displays information about the PenMount controller and driver version. (Fig.17)




Fig.16



Fig.17

3.1.1.2 Multiple Monitors

Multiple Monitors supports two to four touch screen displays on one system. Each monitor requires its own PenMount PCI control board, either installed inside the display or in a central unit. The PenMount PCI control boards must be connected to the computer's RS-232 or USB ports. Driver installation procedures are the same as installation procedures for a single monitor.

Before using Multiple Monitors, you must have two or more monitors that are in extension mode. For display cards that support multiple monitors, we recommend using Matrox, nVidia, or ATI products and inquiring about operation and usability issues in advance.

Note:

- The Multiple Monitors function is for use with multiple displays only. Do not use this function if you have only one touch screen display. Please note once you turn on this function, the Rotating function will be disabled.
- Before using multiple monitors, you need to map each monitor.

Follow the steps below to enable multiple displays:

Step 1: In PenMount Control Panel, under the Multiple Monitors tab, check the "Multiple Monitor Support" box.

Then click "Map Touch screens" to assign touch controllers to displays. (Fig.18)

Step 2: When the mapping screen message appears, click "OK". (Fig.19)

Step 3: Touch each screen when it displays the message "Please touch this monitor. Press 'S' to skip. Follow this sequence and touch each screen to map the touch screens. (Fig.20)




Fig.18




Fig.19




Fig.20

Note:

- If you change the resolution of displays or their screen address, you have to perform "Map Touch screens" again so the system can identify where the displays are.
- If you have multiple monitors but only one touch screen, press "S" to skip the mapping step.

Step 4: For example, with two Touch Monitors connected, please make sure the touch monitors are plugged in and detected. (Fig.21 & 22)

Step 5: In PenMount Control Panel, in the Multiple Monitors tab, click "Map Touch screens," then click "OK". (Fig.23)




Fig.21



Fig.22




Fig.23

Step 6: Please follow the instructions shown on the display to match controllers and the touch screens. Click "S"

to skip this step if the first monitor is not being used as a touch screen. (Fig.24)

Step 7: When the screen switches to Screen 2, please touch it. If screen 2 has no touch function, press “S” to skip it. (Fig.25)



Fig.24



Fig.25

3.1.1.3 Tools

The buttons on “PenMount Control Panel” have the following functions: (Fig.26)




Fig.26

Draw :	Tests or demonstrates PenMount touch screen operation.
Right Button Icon :	Enables right button function. The icon can be shown on the Desktop or in the notification area.
Double Click Speed :	Adjusts Double click operation speed.

3.1.1.4 Screen Rotation Monitor

This function supports nVidia, Intel, or ATI rotation auto-detection.

3.1.2 PenMount monitor menu icon

The PenMount Monitor icon (PM) appears in the notification area of Windows XP systems when you turn on PenMount Monitor in the PenMount utility. (Fig.27)



Fig.27

PenMount Monitor has the following functions: (Fig.28)




Fig.28

Control Panel:	PenMount Control Panel.
Beep:	Beep setting for each device.
Right Button:	When this function is selected, a mouse icon appears in the upper right of the screen. Click this icon to switch between Right and Left Button functions.
Exit:	Exits the PenMount Monitor.

3.2 Configure PenMount PCI RS-232/USB In Windows Vista/7

Double-click on the “PenMount Control Panel” icon on the Desktop to open the configuration utility. (Fig.29) On the “PenMount Control Panel”, you will see the icon for PenMount PCI RS-232 (or USB) under the Device tab. In the “Device” tab, you can see the “devices” detected on your system. Select a device and press the “Configure” button to configure it.



Fig.29

3.2.1 PenMount Control Panel

The functions of PenMount Control Panel are:

3.2.1.1 Device

In this tab, you see how many devices are detected on your system. Select any device by clicking on its icon. (Fig.30)

a. Edge Compensation

The edge compensation settings allow for advanced calibration. You can adjust the settings from 0 to 30 to accommodate the differences of each touch panel. (Fig.31)

b. About

This panel displays information about the PenMount controller and driver version. (Fig.32)




Fig.30




Fig.31




Fig.32

3.2.1.2 Tools




Fig.33

a. Draw

The Draw tool tests or demonstrates PenMount touch screen operation. (Fig.33)

3.2.2 Multiple Monitors

In the Windows Vista/7 environment, if you installed the PenMount controller as a digitizer device, you will need to use Multiple Monitor control functions provided by Microsoft to set the touch panel and monitor pairings. Here are the operating steps (Fig.34):

Step 1: Open Control Panel

Step 2: Find Tablet PC Settings and click

Step 3: Hit Setup Button

Touch each screen when it displays “If this is not the Tablet PC screen. Press Enter to move to the next screen. To close the tool, press Esc.” Follow the sequence and touch each screen to map all the touch screens. (Fig.35)




Fig.34



Fig.35

Chapter 4 PenMount Utilities

To provide customers with comprehensive support services, we offer different utilities to distributors, system integrators, and end users, allowing for the easy use of PenMount PCI solutions. There are two series of PenMount Utilities depending on the operating system supported.

- PenMount Utilities for Windows: PCIMSet, PCIQuickSet, PMUpdate
- PenMount Utilities for Linux: PmFu, PCIMSet

This chapter introduces the functions and applicable users for each utility.

4.1 PenMount utilities for Windows

4.1.1 PCIMSet

PCIMSet is mainly provided to distributors or system integrators. PCIMSet can be used to modify parameter settings of controller firmware and verify controller firmware information such as its version. PCIMSet contains four tabs: Common, Sensitivity, Parameters, and Panel. The function of each tab is explained below:

- Common: This tab shows firmware version, panel size, cover glass thickness, and interface; it can also compute standard deviation for the current environment. (Fig.36)
- Sensitivity: This tab allows the user to adjust the sensitivity of the controller. (Fig.37)




Fig.36




Fig.37

- Parameters: The user can change parameter settings in this tab, including single or dual-touch, touch panel orientation, interface setting, and edge compensation. (Fig.38)
- Panel: Users can modify touch panel size and cover lens thickness in this tab. (Fig.39)




Fig.38




Fig.39

Note: Please refer to the PCIMSet User Guide contained in the PCIMSet Utility compressed file for detailed instructions on how to use PCIMSet.

4.1.2 PCIQuickSet

PCIQuickSet is provided to customers. User can modify parameter settings of the controller firmware and verify controller firmware information such as its version. PCIQuickSet contains three tabs: Common, Parameters, and Edge Compensation. The function of each tab is explained below:

- Common: This tab shows firmware version, panel size, cover glass thickness, and interface. (Fig.40)
- Parameters: The user can change parameter settings in this tab, including single or dual-touch, touch panel orientation, and sensitivity. (Fig.41)
- Edge Compensation: This feature allows the user to adjust edge compensation. (Fig.42)




Fig.40




Fig.41




Fig.42

Note: Please refer to the PCIQuickSet User Guide contained in the PCIQuickSet Utility compressed file for detailed instructions on how to use PCIQuickSet.

4.1.3 PMUpdate

PMUpdate allows users to update controller firmware version and modify or save controller firmware settings. PMUpdate contains three tabs: Field Update and Parameter Update, Field Update Only, and Parameter Update Only. The function of each tab is explained below:

- Field Update and Parameter Update: User can modify the firmware and modify or save controller parameter settings. (Fig.43)




Fig.43

- Field Update Only: User can modify firmware settings. (Fig.44)




Fig.44

- Parameter Update Only: User can modify or save controller parameter settings. (Fig.45)




Fig.45

Note: Please refer to the PMUpdate User Guide contained in the PMUpdate Utility compressed file for detailed instructions on how to use PMUpdate.

4.2 PenMount utilities for Linux

4.2.1 PCIMSet for Linux

PCIMSet is provided to distributors or system integrators. PCIMSet allows users to modify controller firmware parameter settings and verify controller firmware information such as its version. PCIMSet provides four functions: Display controller information, Specify sensor size and cover lens, Change touch parameters, and Advanced settings.

- Display controller information: This function allows the user to verify controller firmware version, panel size, cover lens thickness, and controller interface. (Fig.46)
- Specify sensor size and cover lens: User can modify panel size and cover lens thickness. (Fig.47)

```
[Main Menu]
=====
1. Display controller information
2. Specify sensor size and cover lens
3. Change touch parameters
4. Advanced settings
-----
5. Save changes And Exit
Q. Cancel changes and Exit
=====

Please select next action : 1

[PenMount Device Settings]
=====
Device       : PM1300A Control Board
Location     : USB 3-1
Firmware     : 1.8 (build 2)
Boot Version : 1.8A (build 1)
Panel Size   : 8.4 inch
Cover Lens   : 1.1 mm (Glass)
=====
```

Fig.46

```
[Main Menu]
=====
1. Display controller information
2. Specify sensor size and cover lens
3. Change touch parameters
4. Advanced settings
-----
5. Save changes And Exit
Q. Cancel changes and Exit
=====

Please select next action : 2

[Specify Touch Sensor Settings]
=====
1. Change Panel Size : 8.4 inch
2. Change Cover Lens : 1.1 mm (Glass)
-----
Q. Exit to upper menu
=====

Please select action : █
```

Fig.47

- Change touch parameters: User can modify settings for single or dual touch, panel orientation, and edge compensation. (Fig.48)
- Advanced settings: User can modify the interface and adjust sensitivity. (Fig.49)

```
[Main Menu]
=====
1. Display controller information
2. Specify sensor size and cover lens
3. Change touch parameters
4. Advanced settings
-----
5. Save changes And Exit
Q. Cancel changes and Exit
=====

Please select next action : 3

[Change Touch Parameters]
=====
1. Single Touch Mode   : no
2. Reverse X & Y Axis  : no
3. Edge Adjust (Left)  : 2
4. Edge Adjust (Right) : 2
5. Edge Adjust (Up)    : 2
6. Edge Adjust (Down)  : 2
-----
Q. Exit to upper menu
=====

Please select action : █
```

Fig.48

```
[Main Menu]
=====
1. Display controller information
2. Specify sensor size and cover lens
3. Change touch parameters
4. Advanced settings
-----
5. Save changes And Exit
Q. Cancel changes and Exit
=====

Please select next action : 4

[Advanced Settings]
=====
1. Host Connection     : USB
2. Sensitivity         : 2
-----
Q. Exit to upper menu
=====

Please select action : █
```

Fig.49

Note: Please refer to the PCIMSet for Linux User Guide attached in the PCIMSet Utility compressed file for details on operation.

4.2.2 PmFu for Linux

PmFu allows users to update the firmware. The following window will appear after the file is opened (Fig.50). Select the corresponding firmware to update.

```
test@test-G33-DS3R: ~/PCI FW
test@test-G33-DS3R:~/PCI FW$ sudo ./pmfu
=====
|           PenMount Firmware Update Utility           |
=====
[pmfu] Version 1.2 (Beta 3)

Please choose a firmware file listed below :
[0] PM1300A_V18.pmf
[1] PM2201_V18.pmf
[2] PM1500_V11.pmc
[3] PM1500_V10.pmc
[4] PM1301_V10.pmf
[5] PM1400A_V10.pmc
[6] PM2201_V17.pmf
[7] PM1300A_V17.pmf
[8] PM1400A_V12.pmc
[9] PM2101_V18.pmf
[10] PM2101_V19.pmf
[11] PM1400A_V13.pmc
[12] PM2201_V19.pmf
[13] PM2201_V20.pmf
[14] PM1400A_V11.pmc
[15] PM1300A_V16.pmf
[16] PM2101_V20.pmf
[17] PM1301_V11.pmf
[18] PM2101_V17.pmf
```

Fig.50

Note: Please refer to the PmFu for Linux User Guide attached in the PmFu Utility compressed file for details on operation.

Chapter 5 Trouble Shooting

1. What is the structure of AMT PCI touch sensors?

The current AMT PCI sensor structures consist of either two or three layers of ITO film laminated to the glass top panel, otherwise known as GFF (Glass-Film-Film) or GFFF (Glass-Film-Film-Film) types.

2. What is the purpose of the PCI touch sensor's rear conductive layer?

The bottom conductive film layer of the PCI touch panel is for EMI shielding purposes; the EMI shielding layer blocks system or LCD noise and ensures accurate detection of signals.

3. What is the bending radius of the PCI tail? Is there anything in particular we should take note of for the tail?

The tail's bending radius is 1mm. The PCI touch panel is sensitive to noise. If the tail gets too close to or come into contact with the bezel or metal case, it will cause interference to PCI touch detection.

4. What is the surface hardness of the PCI panel?

The surface of the PCI panel is cover glass with a hardness of MOHS 5.

5. Do AMT PCI solutions operate on Windows 7 and Windows 8?

Yes, AMT PCI USB products use the Windows 7 or Windows 8 inbox driver.
For AMT PCI RS232 products, please install the PenMount Universal Driver.

6. What should the length of the tail be on the PCI touch sensor?

The shorter the better. A shorter tail reduces interferences between electronic components.

7. What kinds of surface treatments are available for PCI touch sensors?

Clear, AG (Antiglare), AR (Anti-reflection), and AS (Anti-smudge).

8. Can a projected capacitive touch screen be operated when there is liquid on its surface?

Sometimes liquid on the surface of a projected capacitive touch screen might cause a malfunction, which is a limit yet to be overcome by projected capacitive touch technology. When there is water on the surface of the PCI touch panel, please wipe it dry. Then PCI will function properly.

9. Can I operate a projected capacitive touch screen with gloved fingers?

AMT PCI touch panels with PenMount PCI control boards are able to support gloved finger operation by certain kinds of gloves including latex gloves for medical and clean rooms, household latex gloves, cotton gloves, and work gloves.

10. Is it ok if there are objects on the surface of the touch panel while rebooting?

When the system is rebooting, no objects (such as hands) should be on the surface of the touch sensor.

11. What capacitance technology do PenMount projected capacitive touch controllers employ?

PenMount projected capacitive touch controllers are based on mutual capacitance technology and locate touches with driving and sensing lines laid out on the two conductive layers of the touch sensor.

12. Do PenMount's projected capacitive touch controllers work with touch sensors made by other manufacturers?

PenMount's projected capacitive touch controllers can work with any touch sensors designed to meet the requirements of PenMount controllers. Please contact our sales staff for further information.

13. If customers would like to design a PCI IC onto their system main board, can AMT support this kind of design?

In general, we are able to support customers' designed PCI IC on their system main board. Please contact our sales staff.

14. Which hardware platforms do PenMount PCI drivers support?

All PenMount PCI drivers are based on the x86 system and ARM-based Linux embedded system. Please contact our sales staff for other hardware platform requirements.

15. Will PenMount support ARM-based Linux and Android OS? Can PenMount provide the drivers?

Yes. If you use the ARM hardware platform, it employs Reduced Instruction Set Computing (RISC). You can contact our sales staff with your requirements. You will need to fill out company profile information and sign a NDA. PenMount will provide source code for you to successfully develop drivers for our PenMount devices.

16. How do I enable multi-touch on Linux or Android?

For Linux, PenMount USB devices are supported by the inbox driver of Linux Kernel 3.0, and PenMount RS232 interface is supported by the inbox driver of Linux kernel 3.2.

For other Linux and Android operating systems, you can drive PenMount hardware devices with PenMount driver source code and enable multi-touch functionality with Linux/Android multi-touch application programs.